



Register Descriptions

Register	Upper Byte	Lower Byte	Commands	Type
1		Bit 0: Start/Stop	03, 06, 08	R/W
2		Motor Speed (0-100%)	03, 06, 08	R/W
3	P Value		03, 06, 08	R/W
4	I Value		03, 06, 08	R/W
5	D Value		03, 06, 08	R/W
6	Motor Speed (RPM)		03	R
7	Analog Input (0-1023)		03	R
8	Minimum Speed Pot (0-1023)		03	R
9	Configuration Jumpers		03	R
10		Default Speed (0-100%)	06	R/W
11	Version Major	Version Minor	03	R
12				
13				
14		Bit 0: Default Start/Stop	06	R/W
15		Group 1 Address	06	R/W
16		Group 2 Address	06	R/W
17				
18				

Key

Assigned Byte
Unused